

## ArcPad Xtreme (RGBCW) - DMX protocol

Version 1.0

Mode/Channel						Value	Function	Type of control
1	2*	3	4	5	6			
-	1	1	1	-	-	0 - 255	<b>Red LEDs - both LED modules</b> Red LEDs saturation control (0-100%)	proportional
-	2	2	2	-	-	0 - 255	<b>Green LEDs - both LED modules</b> Green LEDs saturation control (0-100%)	proportional
-	3	3	3	-	-	0 - 255	<b>Blue LEDs - both LED modules</b> Blue LEDs saturation control (0-100%)	proportional
-	-	4	4	-	-	0 - 255	<b>White LEDs - both LED modules</b> White LEDs saturation control (0-100%)	proportional
-	-	-	-	1	1	0 - 255	<b>Red LEDs – LED module 1</b> Red LEDs saturation control (0-100%)	proportional
-	-	-	-	2	2	0 - 255	<b>Green LEDs - LED module 1</b> Green LEDs saturation control (0-100%)	proportional
-	-	-	-	3	3	0 - 255	<b>Blue LEDs - LED module 1</b> Blue LEDs saturation control (0-100%)	proportional
-	-	-	-	4	4	0 - 255	<b>White LEDs - LED module 1</b> White LEDs saturation control (0-100%)	proportional
-	-	-	-	5	5	0 - 255	<b>Red LEDs - LED module 2</b> Red LEDs saturation control (0-100%)	proportional
-	-	-	-	6	6	0 - 255	<b>Green LEDs - LED module 2</b> Green LEDs saturation control (0-100%)	proportional
-	-	-	-	7	7	0 - 255	<b>Blue LEDs - LED module 2</b> Blue LEDs saturation control (0-100%)	proportional
-	-	-	-	8	8	0 - 255	<b>White LEDs - LED module 2</b> White LEDs saturation control (0-100%)	proportional
1	-	-	5	-	9	0 1-15 16 17-55 56 57 - 95 96 97 – 134 135 136 - 174 175 176 -214 215	<b>Colour macros (255 values) – both LED modules</b> No function (for DMX mode 4 and 6) White (for DMX mode 1) White tones (cool→warm) <b>Blue</b> (Blue=full, Red+Green+White=0) Red=0, Green→up, Blue =full, White=0 <b>Light Blue</b> (Red=0, Green=full, Blue =full, White=0) Red=0, Green=full, Blue→down, White=0 <b>Green</b> (Red=0, Green=full, Blue =0, White=0) Red→up, Green=full, Blue=0, White=0 <b>Yellow</b> (Red=full, Green=full, Blue=0, White=0) Red=full, Green→down, Blue=0, White=0 <b>Red</b> (Red=full, Green=0, Blue=0, White=0) Red=full, Green=0, Blue→up, White=0 <b>Magenta</b> (Red=full, Green=0, Blue=full, White=0)	step proportional step proportional step proportional step proportional step proportional step

## ArcPad Extreme

Mode/Channel						Value	Function	Type of control
1	2*	3	4	5	6			
1	-	-	5	-	9	216 - 254 255	<b><u>Colour macros – both LED modules</u></b> Red→down, Green=0, Blue=full, White=0 <b>Blue</b> (Red=0, Green=0, Blue=full, White=0)	proportional step
-	-	-	6	-	10	0-31 32-63 64-95 96-127 128-143 144-159 160-191 192-223 224-255	<b><u>Shutter/ Strobe – both LED modules</u></b> Shutter closed Shutter open Strobe-effect from slow to fast Shutter open Opening pulses in sequences slow--> fast Closing pulses in sequences fast --> slow Shutter open Random strobe-effects from slow to fast Shutter open	step step proportional step proportional proportional step proportional step
2	-	-	7	-	11	0 - 255	<b><u>Dimmer – both LED modules</u></b> Dimmer intensity from 0% to 100%	proportional
-	-	-	8	-	12	0 - 255	<b><u>Dimmer fine – both LED modules</u></b> Fine dimmer intensity from low to high	proportional

\*White LEDs lit proportionally when Red+Green+Blue LEDs are saturated together.