ArcPower Micro 270 - DMX protocol

version 2.0 (software version 1.3 and higher)

Mode/ Channel		Value	Function	Type of control
1	2			
1	1	0-255	**RED LED** Red LED saturation control (0-100%)	proportional
2	2	0-255	**GREEN LED** Green LED saturation control (0-100%)	proportional
3	3	0-255	**BLUE LED** Blue LED saturation control (0-100%)	proportional
	4		**MACRO SELECTION**	
		0-7	No function	step
		8-15	Macro 1	step
		16-23	Macro 2	step
		24-39	Macro 3	step
		40-47	Macro 4	step
		48-55	Macro 5	step
		56-68	Macro 6	step
		69-71	Macro 7	step
		72-79	Macro 8	step
		80-87	Macro 9	step
		88-95	Macro 10	step
		96-103	Macro 11	step
		104-111	Macro 12	step
		112-119	Macro 13	step
		120-127	Macro 14	step
		128-135	Macro 15	step
		136-143	Macro 16	step
		142-151	Macro 17	step
		152-159	Macro 18	step
		160-167	Macro 19	step
		168-175	Macro 20	step
		176-183	Macro 21	step
		184-191	Macro 22	step
		192-199	Macro 23	step
		200-207	Macro 24	step
		208-215	Macro 25	step
		216-223	Macro 26	step
		224-231	Macro 27	step
		232-239	Macro 28	step
		240-247	Macro 29	step
		248-255	Rainbow effect with variable speed	proportional
	5		**SHUTTER/STROBE**	
		0-31	Shutter closed	step
		32-63	Shutter open	step
		64-95	Strobe-effect from slow to fast	proportional
		96-127	Shutter open	step
		128-143	Opening pulses in sequences slow--> fast	proportional
		144-159	Closing pulses in sequences fast --> slow	proportional
		160-191	Shutter open	step
		192-223	Random strobe-effects from slow to fast	proportional
		224-255	Shutter open	step
	6	0-255	**DIMMER** Dimmer intensity from 0% to 100%	proportional